

### UHF-M3: 692 - 716 MHz, Group 1-10

	Group 1	Group 2	Group 3	Group 4	Group 5	Group 6	Group 7	Group 8	Group 9	Group 10
1	692,500	692,125	692,250	698,250	692,500	692,125	692,125	715,625	715,500	715,125
2	693,375	692,625	695,125	698,875	693,250	693,500	693,125	714,625	714,250	714,125
3	694,500	693,375	695,875	700,000	694,250	694,125	693,625	714,000	712,750	713,625
4	695,000	694,375	697,125	700,625	695,000	695,125	694,625	713,125	712,000	711,875
5	697,000	695,125	698,625	701,500	695,500	695,750	695,875	712,000	710,875	711,125
6	698,000	698,875	699,875	702,000	696,250	697,000	696,500	710,250	710,375	709,875
7	699,250	699,375	700,625	702,750	697,250	697,750	697,875	708,125	708,250	709,000
8	699,750	700,625	701,625	703,750	698,000	699,125	698,875	707,625	707,125	708,375
9	702,875	703,125	702,375	704,375	704,500	700,125	700,500	706,750	704,125	707,375
10	703,750	704,625	703,625	709,000	706,000	701,625	701,500	706,250	702,500	706,625
11	705,500	706,375	704,375	709,500	706,750	702,250	703,375	703,625	700,625	705,125
12	707,500	707,125	708,375	710,250	707,250	710,125	703,875	702,625	699,000	700,875
13	708,500	707,625	709,375	711,250	708,750	710,625	705,875	701,875	698,125	700,000
14	709,000	708,375	709,875	711,875	709,500	711,500	706,875	699,875	697,625	699,375
15	709,750	710,875	710,750	712,750	711,250	712,125	707,625	696,375	695,875	697,625
16	710,250	711,500	711,875	713,250	712,000	713,125	708,125	695,875	694,875	696,875
17	712,750	712,500	713,375	714,000	713,250	713,875	709,125	694,625	694,375	696,375
18	713,750	713,125	714,125	715,000	714,250	714,375	709,625	693,750	693,250	694,625
19	714,500	714,375	714,625	715,625	715,000	715,250		692,375	692,500	694,125
20	715,500	715,125	715,625		716,000	715,875				693,125
21										
22										
23										
24										
25										
26										
27										
28										
29										
30										
31										
Explanation of group content	Current UB group 1	Current UB group 2	Current UB group 3	Current UB group 4	Current UB group 5	Current UB group 6	Current UB group 7	Current UB group 8	Current UB group 9	Current UB group 10
Results for M3										
For use in ...	UB/M3 setups	UB/M3 setups	UB/M3 setups	UB/M3 setups	UB/M3 setups	UB/M3 setups	UB/M3 setups	UB/M3 setups	UB/M3 setups	UB/M3 setups

### UHF-M3: 692 - 716 MHz, Group 11-20

	Group 11	Group 12	Group 13	Group 14	Group 15	Group 16	Group 17	Group 18	Group 19	Group 20
1	692,250	715,500	692,500	714,975	692,000	716,000	692,875	692,275	692,250	715,500
2	695,250	714,500	693,300	712,775	692,700	714,775	693,625	693,025	695,750	714,500
3	695,750	713,250	694,500	712,025	694,300	712,975	694,675	694,075	697,250	713,250
4	697,250	712,500	696,025	709,700	695,000	712,225	695,575	694,975	697,750	712,500
5	698,500	711,500	696,775	708,500	696,225	710,300	696,025	695,425	698,500	711,500
6	699,500	710,750	698,225	706,225	696,975	709,100	696,925	696,325	699,500	710,750
7	700,250	707,750	701,700	702,500	700,000	703,000	697,675	697,075	700,250	707,750
8	702,750	707,250	702,500	701,700	700,700	701,900	698,125	697,525	703,500	707,250
9	703,500	705,750	706,225	701,300	706,775	700,000	698,875	698,275	704,500	705,750
10	704,500	705,250	708,500	698,225	709,100	698,775	699,475	698,875	705,250	705,250
11	705,750	704,500	709,300	696,775	710,300	696,225	699,925	699,325	705,750	703,500
12	707,250	703,500	709,700	696,025	711,000	695,000	700,525	699,925	707,250	699,500
13	707,750	699,500	712,775	694,500	712,225	694,300	701,425	700,825	707,750	698,500
14	710,750	698,500	713,500	693,300	714,775	692,700	701,875	701,275	710,750	697,750
15	711,500	697,750	714,975	692,500	716,000	692,000	702,775	702,175	711,500	696,500
16	712,500	695,250					704,575	703,975	712,500	695,750
17	714,500	694,750					705,775	705,175	714,500	694,750
18	715,500	692,250					707,575	706,975	715,500	692,250
19							708,475	707,875		
20							708,925	708,325		
21							709,825	709,225		
22							710,425	709,825		
23							711,325	710,725		
24							711,775	711,175		
25							712,525	711,925		
26							712,975	712,375		
27							714,025	713,425		
28							714,775	714,175		
29							715,375	714,775		
30							715,825	715,225		
31										
Explanation of group content	France preferred: User Group A 1. option	France preferred: User Group A 2. option	France preferred: User Group B 1. option	France preferred: User Group B 2. option	France preferred: User Group C 1. option	France preferred: User Group C 2. option	Full Range, max. # of compatible frequencies	Full Range, max. # of compatible frequencies	France preferred: User Group A 1. option	France preferred: User Group A 2. option
Results for MK2							max. number	group17 - 600kHz	max. number	17% dif. to grp.19.
For use in ...	UB/M3 setups	UB/M3 setups	UB/M3 setups	UB/M3 setups	UB/M3 setups	UB/M3 setups	M3 setups only	M3 setups only	M3 setups only	M3 setups only

### UHF-M3: 692 - 716 MHz, Group 21-27

	Group 21	Group 22	Group 23	Group 24	Group 25	Group 26	Group 27
1	693,300	714,975	693,100	714,775	692,150	692,600	710,150
2	693,700	712,025	693,900	712,975	692,600	692,975	710,600
3	694,500	710,100	694,300	712,225	694,000	694,450	710,900
4	696,775	709,700	695,000	709,900	694,900	695,125	711,500
5	698,225	708,900	698,025	709,100	695,650	695,575	711,800
6	700,500	708,500	698,775	708,700	696,100	696,550	712,250
7	700,900	706,225	700,000	708,000	697,000	697,075	713,300
8	702,100	704,775	700,700	704,225	697,450	698,350	714,200
9	702,500	701,700	702,300	702,300	698,050	698,875	714,650
10	706,975	700,900	708,000	700,700	698,500	699,175	714,950
11	708,900	698,975	708,700	700,000	699,400	699,850	715,475
12	709,300	698,225	709,100	698,775	699,850	700,300	715,850
13	710,100	696,775	709,900	698,025	704,250	704,325	
14	712,025	696,025	712,225	695,000	705,000	705,975	
15	712,775	694,100	712,975	694,300	705,450	706,575	
16	714,225	692,500	714,025	693,900	706,800	707,325	
17			714,775	693,100	707,400	708,525	
18					708,300	710,075	
19					710,900	710,825	
20					711,350	711,425	
21					712,100	711,800	
22					712,700	712,475	
23					713,150	713,750	
24					714,650	714,650	
25					715,700	715,250	
26							
27							
28							
29							
30							
31							
Explanation of group content	France preferred: User Group B 1. option	France preferred: User Group B 2. option	France preferred: User Group C 1. option	France preferred: User Group C 2. option	Germany preferred: Broadcaster 1.option	Germany preferred: Broadcaster 2.option	Belgium preferred: 710.000 - 716.000 MHz
Results for MK2	max. number	63% dif. to grp.21	max. number	6% dif. to grp.23	max. number	88% dif. to grp.25	max. number
For use in ...	M3 setups only	M3 setups only	M3 setups only	M3 setups only	M3 setups only	M3 setups only	M3 setups only

### UHF-R3: 774 - 782 MHz, Group 1-10

	Group 1	Group 2	Group 3	Group 4	Group 5	Group 6	Group 7	Group 8	Group 9	Group 10
1	774,125	774,250	774,375	774,125	774,250	774,250	774,375	774,250	774,100	774,250
2	775,125	775,250	775,125	774,625	775,000	775,000	775,375	774,750	774,400	774,550
3	775,625	775,750	776,125	775,625	776,000	775,500	775,875	775,750	775,075	775,150
4	776,375	776,500	776,875	776,375	776,750	776,250	776,625	776,500	775,375	775,450
5	777,375	777,500	777,375	776,875	777,250	777,250	777,625	777,000	775,900	775,900
6	778,000	778,125	778,250	777,750	778,125	777,875	778,250	777,875	776,200	776,200
7	778,875	779,000	778,875	778,375	778,750	778,750	779,125	778,500	776,875	776,800
8	779,375	779,500	779,875	779,375	779,750	779,250	779,625	779,500	777,175	777,100
9	780,125	780,250	780,625	780,125	780,500	780,000	780,375	780,250	778,825	778,600
10	781,125	781,250	781,125	780,625	781,000	781,000	781,375	780,750	779,125	778,900
11	781,625	781,750	781,875	781,625	781,750	781,750	781,875	781,750	779,800	779,500
12									780,100	779,800
13									780,625	780,250
14									780,925	780,550
15									781,600	781,150
16									781,900	781,450
17										
18										
19										
20										
21										
22										
23										
24										
25										
26										
27										
28										
29										
30										
31										
Explanation of group content	Current MC	Current MC	Current MC	Current MC	Current MC	Current MC	Current MC	Current MC	Full Range, max. # of compatible frequencies	Full Range, max. # of compatible frequencies
	group 1	group 2	group 3	group 4	group 5	group 6	group 7	group 8		
Results for MK2									max. number	81% dif. to grp.9
For use in ...	MC/R3 setups	MC/R3 setups	MC/R3 setups	MC/R3 setups	MC/R3 setups	MC/R3 setups	MC/R3 setups	MC/R3 setups	R3 setups only	R3 setups only

### UHF-R3: 774 - 782 MHz, Group 11-18

	Group 11	Group 12	Group 13	Group 14	Group 15	Group 16	Group 17	Group 18
1	774,025	774,025	774,100	774,350	774,200	774,750	774,100	774,300
2	774,325	774,325	774,550	774,950	774,500	775,500	774,500	775,000
3	774,925	775,000	774,850	775,250	774,950	776,500	778,225	776,225
4	775,225	775,525	775,300	775,850	775,250	777,250	778,975	776,975
5	775,675	775,825	775,900	776,300	776,150	777,750	780,500	778,775
6	775,975	776,425	776,350	776,900	776,525	778,500	781,300	780,000
7	776,575	776,875	776,650	777,200	777,200	779,500	781,700	781,500
8	776,875	777,175	777,550	777,800	778,700	780,250		781,900
9	778,675	778,075	778,900	779,000	779,300			
10	779,275	779,125	779,350	779,600	779,750			
11	779,575	779,575	779,950	779,900	780,050			
12	780,025	779,875	780,400	780,500	780,500			
13	780,625	780,475	780,700	780,950	781,100			
14	781,000	780,925	781,300	781,550	781,550			
15	781,525	781,525	781,675	781,850	781,850			
16	781,825							
17								
18								
19								
20								
21								
22								
23								
24								
25								
26								
27								
28								
29								
30								
31								
Explanation of group content	Full Range, max. # of compatible frequencies	Full Range, max. # of compatible frequencies	Full Range, max. # of compatible frequencies	Full Range, max. # of compatible frequencies	Full Range, max. # of compatible frequencies	France preferred: User Group A	France preferred: User Group B	France preferred: User Group C
Results for MK2	88% dif. to grp.9	31% dif. to grp.9	63% dif. to grp.9	94% dif. to grp.9	94% dif. to grp.9	max. number	max. number	max. number
For use in ...	R3 setups only	R3 setups only	R3 setups only	R3 setups only	R3 setups only	R3 setups only	R3 setups only	R3 setups only

### UHF-R7: 782 - 810 MHz, Group 1-10

	Group 1	Group 2	Group 3	Group 4	Group 5	Group 6	Group 7	Group 8	Group 9	Group 10
1	782,250	782,500	783,250	<b>783,750</b>	<b>809,250</b>	<b>782,100</b>	<b>809,500</b>	<b>782,300</b>	<b>808,225</b>	<b>782,175</b>
2	782,875	783,625	784,750	<b>784,500</b>	<b>808,500</b>	<b>784,025</b>	<b>808,775</b>	<b>783,000</b>	<b>807,000</b>	<b>782,775</b>
3	784,625	784,125	785,500	<b>786,500</b>	<b>807,250</b>	<b>784,775</b>	<b>806,500</b>	<b>784,225</b>	<b>806,300</b>	<b>783,675</b>
4	785,250	785,125	787,500	<b>787,500</b>	<b>806,750</b>	<b>786,225</b>	<b>805,700</b>	<b>784,975</b>	<b>804,700</b>	<b>785,025</b>
5	787,250	786,375	788,375	<b>790,750</b>	<b>803,750</b>	<b>788,900</b>	<b>805,300</b>	<b>788,000</b>	<b>804,000</b>	<b>785,775</b>
6	788,750	788,375	789,000	<b>791,750</b>	<b>803,250</b>	<b>790,100</b>	<b>804,500</b>	<b>788,700</b>	<b>802,775</b>	<b>786,225</b>
7	790,750	788,875	791,500	<b>793,250</b>	<b>801,750</b>	<b>792,025</b>	<b>802,975</b>	<b>789,900</b>	<b>798,300</b>	<b>788,025</b>
8	791,250	790,750	792,250	<b>793,750</b>	<b>801,250</b>	<b>792,775</b>	<b>802,225</b>	<b>797,100</b>	<b>796,700</b>	<b>789,525</b>
9	792,500	792,375	792,750	<b>794,500</b>	<b>800,500</b>	<b>796,900</b>	<b>798,500</b>	<b>798,300</b>	<b>794,775</b>	<b>790,725</b>
10	794,875	793,375	793,750	<b>795,500</b>	<b>799,500</b>	<b>798,500</b>	<b>796,900</b>	<b>800,225</b>	<b>792,225</b>	<b>791,175</b>
11	795,500	794,625	794,375	<b>796,250</b>	<b>795,500</b>	<b>802,225</b>	<b>792,775</b>	<b>800,975</b>	<b>791,000</b>	<b>791,775</b>
12	796,625	798,125	796,750	<b>799,500</b>	<b>794,500</b>	<b>802,975</b>	<b>792,025</b>	<b>804,000</b>	<b>789,100</b>	<b>792,225</b>
13	800,000	799,375	797,750	<b>800,500</b>	<b>791,250</b>	<b>804,500</b>	<b>790,100</b>	<b>805,100</b>	<b>788,000</b>	<b>793,125</b>
14	801,750	799,875	801,500	<b>801,250</b>	<b>790,750</b>	<b>805,700</b>	<b>788,900</b>	<b>805,900</b>	<b>784,225</b>	<b>793,575</b>
15	803,000	801,375	803,000	<b>803,250</b>	<b>788,250</b>	<b>806,500</b>	<b>786,225</b>	<b>808,225</b>	<b>783,000</b>	<b>794,625</b>
16	804,000	802,000	803,500	<b>804,250</b>	<b>787,500</b>	<b>808,775</b>	<b>784,775</b>	<b>808,975</b>	<b>782,300</b>	<b>795,825</b>
17	804,750	803,625	804,750	<b>806,750</b>	<b>786,500</b>	<b>809,500</b>	<b>782,100</b>			<b>797,175</b>
18	807,125	804,875	806,750	<b>807,500</b>	<b>784,500</b>					<b>797,925</b>
19	808,375	807,000	807,500	<b>808,500</b>	<b>783,250</b>					<b>798,375</b>
20	809,000	808,750	809,000	<b>809,750</b>	<b>782,750</b>					<b>800,325</b>
21	809,875	809,625	809,625							<b>801,075</b>
22										<b>801,525</b>
23										<b>802,875</b>
24										<b>803,325</b>
25										<b>803,925</b>
26										<b>805,725</b>
27										<b>806,175</b>
28										<b>806,925</b>
29										<b>809,175</b>
30										<b>809,775</b>
31										
Explanation of group content	Current MA	Current MA	Current MA	France preferred: User Group A 1. option	France preferred: User Group A 2. option	France preferred: User Group B 1. option	France preferred: User Group B 2. option	France preferred: User Group C 1. option	France preferred: User Group C 2. option	Full Range, max. # of compatible frequencies
	group 1	group 2	group 3							
Results for MK2										max. number
For use in ...	MA/R7 setups	MA/R7 setups	MA/R7 setups	MA/R7 setups	MA/R7 setups	MA/R7 setups	MA/R7 setups	MA/R7 setups	MA/R7 setups	R7 setups only

### UHF-R7: 782 - 810 MHz, Group 11-20

	Group 11	Group 12	Group 13	Group 14	Group 15	Group 16	Group 17	Group 18	Group 19	Group 20
1	782,025	782,750	809,750	782,100	809,500	782,300	808,975	790,925	798,900	791,200
2	782,475	783,250	808,500	782,500	808,775	783,000	808,225	791,400	799,475	791,900
3	783,225	784,500	807,500	784,775	806,500	786,025	807,000	792,525	800,625	792,325
4	785,025	786,500	806,750	786,225	805,700	786,775	806,300	793,100	801,125	792,900
5	785,925	787,500	804,250	788,500	805,300	788,700	804,700	793,425	801,450	793,725
6	786,675	788,250	803,250	788,900	802,225	790,300	804,000	793,925	801,925	794,825
7	787,125	790,750	801,250	789,700	800,025	791,000	802,775	795,050	803,050	795,350
8	787,725	791,250	800,500	790,100	798,500	792,225	798,300	795,675	803,575	796,100
9	788,475	794,500	799,500	792,025	796,500	792,975	797,100	800,600	804,800	796,575
10	789,075	795,500	796,250	792,775	792,775	796,700	794,775	801,150	806,850	801,725
11	790,575	799,500	795,500	796,500	792,025	797,100	794,025	802,025	807,475	802,825
12	791,175	800,500	794,500	798,500	790,100	800,225	792,975	802,325	808,650	803,350
13	791,625	801,250	793,750	800,025	789,700	800,975	792,225	803,075	809,175	804,100
14	792,825	801,750	793,250	802,225	788,900	802,775	789,900	804,825	809,475	804,575
15	795,975	803,250	791,750	805,300	788,500	805,100	788,700	805,200	809,975	807,200
16	796,875	803,750	790,750	805,700	786,225	805,900	784,225	805,800		807,900
17	797,625	806,750	787,500	806,500	784,775	806,300	783,000	806,950		808,325
18	798,075	807,250	786,500	808,775	782,500	807,000	782,300	807,475		808,900
19	798,825	808,500	784,500	809,500	782,100			809,425		
20	799,425	809,250	783,750					809,950		
21	800,475									
22	801,075									
23	801,825									
24	802,275									
25	803,025									
26	804,375									
27	805,425									
28	805,875									
29	808,875									
30	809,625									
31										
Explanation of group content	Full Range, max. # of compatible frequencies	France preferred: User Group A 1. option	France preferred: User Group A 2. option	France preferred: User Group B 1. option	France preferred: User Group B 2. option	France preferred: User Group C 1. option	France preferred: User Group C 2. option	Germany preferred: User Group 4 790-810 MHz	Germany preferred: User Group 4 798-810 MHz	Germany preferred: User Group 3A 790-810 MHz
Results for MK2	91% dif. to grp.10	max. number	40% dif. to grp.12	max. number	0% dif. to grp.14	max. number	50% dif. to grp.16	max. #, TV61+	max. #, TV62+	max. #, TV61+
For use in ...	R7 setups only	R7 setups only	R7 setups only	R7 setups only	R7 setups only	R7 setups only	R7 setups only	R7 setups only	R7 setups only	R7 setups only

### UHF-R7: 782 - 810 MHz, Group 21-28

	Group 21	Group 22	Group 23	Group 24	Group 25	Group 26	Group 27	Group 28
1	790,300	790,350	790,400	790,400	790,100	790,100	790,100	782,100
2	791,250	790,750	790,800	790,800	790,500	790,500	790,600	782,400
3	791,950	791,300	791,350	791,350	791,050	791,050	791,575	783,300
4	792,375	792,425	792,475	792,475	791,750	791,750	792,050	783,600
5	792,950	793,000	793,875	793,050	792,175	792,175	792,800	784,050
6	793,775	793,825	794,975	793,875	792,750	792,750	793,325	784,350
7	794,875	794,925	795,500	794,975	793,575	793,575	794,425	784,950
8	795,400	795,450	796,725	795,500	794,675	794,675	795,250	785,250
9	796,150	796,675	797,700	796,725	795,200	795,200	795,825	787,050
10	796,625	797,650	799,350	797,700	795,950	795,950	796,250	787,350
11	798,700	801,825	803,500		796,425	796,425	796,950	787,950
12	801,775	803,450	805,700		797,400	797,400	797,500	788,250
13	803,400	805,650	806,400		797,900	797,900	797,900	788,700
14	804,150	806,350	806,800		803,200			789,000
15	804,625	806,750	808,475		806,100			789,600
16	806,700	807,300	809,050		806,500			789,900
17	807,250	808,425	809,875		807,050			
18	807,950				807,750			
19	808,375				808,175			
20	808,950				808,750			
21					809,575			
22								
23								
24								
25								
26								
27								
28								
29								
30								
31								
Explanation of group content	Germany preferred: User Group 3B 790-810 MHz	Germany preferred: User Group 3C 790-810 MHz	Germany preferred: User Group 3D 790-810 MHz	Germany preferred: User Group 2 790-810 MHz	Germany preferred: User Group 1 790-810 MHz	Germany preferred: User Group 1 790-798 MHz	Germany preferred: User Group 2 790-798 MHz	Broadcasters preferred: TV ch. 60 782-790 MHz
Results for MK2	max. #, TV61+	max. #, TV61+	max. #, TV61+	max. #, TV61+	max. #, TV61+	max. #, TV61	max. #, TV61	max. #, TV60
For use in ...	R7 setups only	R7 setups only	R7 setups only	R7 setups only	R7 setups only	R7 setups only	R7 setups only	R7 setups only

### UHF-R2: 800 - 830 MHz, Group 1-10

	Group 1	Group 2	Group 3	Group 4	Group 5	Group 6	Group 7	Group 8	Group 9	Group 10
1	802,325	802,050	802,300	803,050	803,625	803,375	802,425	802,300	802,200	<b>800,300</b>
2	803,075	802,675	803,925	804,550	804,125	804,500	803,300	803,050	803,100	<b>800,900</b>
3	804,800	804,425	804,925	805,300	805,000	806,875	803,675	804,050	803,500	<b>801,800</b>
4	805,200	805,050	806,175	808,175	807,125	808,000	806,675	806,550	804,300	<b>802,550</b>
5	806,850	807,050	808,175	808,800	808,500	808,875	807,125	807,550	805,900	<b>803,600</b>
6	809,150	808,550	808,675	811,300	808,875	810,125	808,925	808,300	806,700	<b>805,250</b>
7	810,150	810,550	810,550	812,050	809,625	810,625	809,425	808,800	807,100	<b>806,150</b>
8	812,800	811,050	812,175	812,550	811,000	811,875	810,425	809,550	808,000	<b>807,650</b>
9	819,100	812,300	813,175	813,550	811,625	812,875	813,425	810,550	814,100	<b>808,550</b>
10	819,600	814,675	814,425	814,175	816,375	814,625	813,925	811,300	814,600	<b>809,000</b>
11	821,150	815,300	817,925	816,550	818,750	818,125	815,925	811,800	815,700	<b>809,900</b>
12	821,750	816,425	819,175	817,550	819,375	819,500	816,800	813,300	816,100	<b>811,100</b>
13	822,950	819,800	819,675	821,275	820,875	820,125	818,175	819,300	818,400	<b>811,550</b>
14	825,150	821,550	821,175	822,800	821,375	822,625	818,675	819,800	818,800	<b>812,450</b>
15	826,000	822,800	821,800	823,300	822,125	823,125	820,925	821,800	819,600	<b>812,900</b>
16	827,100	823,800	823,425	826,550	822,625	823,875	821,675	822,175		<b>815,150</b>
17	827,600	824,550	824,675	827,300	823,625	825,375	822,050	823,050		<b>815,600</b>
18	828,800	826,925	826,800	828,800	826,125	826,375	822,675	825,675		<b>816,500</b>
19		828,175	828,550		826,875	827,875	825,675	826,050		<b>817,550</b>
20		828,800			827,375	828,625	826,175	827,050		<b>819,350</b>
21		829,675			828,250	829,125	827,675	827,550		<b>819,800</b>
22					829,375	829,875	828,925	828,675		<b>820,850</b>
23										<b>823,700</b>
24										<b>824,300</b>
25										<b>824,750</b>
26										<b>825,650</b>
27										<b>826,400</b>
28										<b>827,300</b>
29										<b>827,900</b>
30										<b>828,350</b>
31										<b>829,550</b>
Explanation of group content	Current MB	Current MB	Current MB	Current MB	Current MB	Current MB	Current MB	Current MB	Current MB	Full Range, max. # of compatible frequencies
	group 1	group 2	group 3	group 4	group 5	group 6	group 7	group 8	group 9	
Results for MK2										max. number
For use in ...	MB/R2 setups	MB/R2 setups	MB/R2 setups	MB/R2 setups	MB/R2 setups	MB/R2 setups	MB/R2 setups	MB/R2 setups	MB/R2 setups	R2 setups only

### UHF-R2: 800 - 830 MHz, Group 11-20

	Group 11	Group 12	Group 13	Group 14	Group 15	Group 16	Group 17	Group 18	Group 19	Group 20
1	800,550	801,350	800,575	800,650	800,650	800,325	800,375	800,425	800,475	800,050
2	801,150	802,400	801,175	801,150	801,125	800,900	800,950	801,000	801,050	800,800
3	802,050	803,300	801,925	801,925	801,450	801,725	801,775	801,825	801,875	801,325
4	802,800	806,150	802,225	802,250	801,925	802,825	802,875	802,925	802,975	802,425
5	803,850	806,750	803,050	803,025	802,550	803,350	803,400	803,450	803,500	803,250
6	805,500	808,850	803,725	803,550	803,025	807,200	804,150	806,750	806,800	803,825
7	806,400	809,300	804,775	806,900	804,775	807,900	805,600	808,425	808,475	804,250
8	807,900	810,050	805,075	807,450	808,575	808,325	806,700	809,000	809,050	804,950
9	808,800	810,500	808,625	808,550	809,175	808,900	808,950	809,825	809,875	805,500
10	809,250	811,400	809,175	809,100	809,925	809,725	809,775	810,925	810,975	808,800
11	810,150	812,600	809,925	809,425	810,250	810,825	811,400	811,450	811,500	809,325
12	811,350	813,050	810,250	809,925	811,050	811,350	812,150	812,675	812,725	810,425
13	811,800	813,650	811,050	811,025	811,625	812,100	812,625	813,650	813,700	811,250
14	812,700	814,100	811,600	811,700	812,775		813,600			811,825
15	813,150	815,000	812,775	812,800	813,150					812,250
16	815,400	815,750	813,100	813,300	813,775					812,950
17	815,850	817,100	813,775							813,500
18	816,750	817,550								
19	817,800	819,800								
20	819,600	820,850								
21	820,050	821,300								
22	821,100	823,100								
23	823,950	823,550								
24	824,550	824,450								
25	825,000	825,200								
26	825,900	826,100								
27	826,650	827,900								
28	827,550	828,800								
29	828,150	829,400								
30	828,600	829,850								
31	829,800									
Explanation of group content	Full Range, max. # of compatible frequencies	Full Range, max. # of compatible frequencies	Germany preferred: User Group 4 800-814 MHz	Germany preferred: User Group 4 800-814 MHz	Germany preferred: User Group 4 800-814 MHz	Germany preferred: User Group 3A 800-814 MHz	Germany preferred: User Group 3B 800-814 MHz	Germany preferred: User Group 3C 800-814 MHz	Germany preferred: User Group 3D 800-814 MHz	Germany preferred: User Group 2 800-814 MHz
Results for MK2	group1 + 200kHz	80% dif. to grp.10	max. number	82% dif. to grp.13	47% dif. to grp.13	max. number	max. number	max. number	max. number	max. number
For use in ...	R2 setups only	R2 setups only	R2 setups only	R2 setups only	R2 setups only	R2 setups only	R2 setups only	R2 setups only	R2 setups only	R2 setups only

### UHF-R2: 800 - 830 MHz, Group 21-25

	Group 21	Group 22	Group 23	Group 24	Group 25
1	800,175	800,025	800,025	806,000	806,000
2	800,750	800,475	800,475	806,450	806,450
3	801,575	801,075	801,075	807,050	807,050
4	802,675	801,525	801,825	807,500	807,500
5	803,200	802,275	803,025	808,250	808,250
6	803,950	802,875	803,925	808,850	808,700
7	804,425	803,925	804,675	809,300	809,300
8	805,900	804,375	805,125	809,900	810,200
9	806,500	806,025	805,875	810,800	810,800
10	809,575	807,075	806,475	811,400	811,250
11	810,675	807,975	806,925	811,850	812,000
12	811,200	808,575	808,125	812,450	812,450
13	811,950	809,025	808,575	813,200	813,050
14	812,425	809,625	809,475	813,650	813,500
15	813,400	810,375	810,075		
16	813,900	810,825	810,975		
17		811,425	811,425		
18		812,325	812,175		
19		812,925	812,625		
20		813,375	813,525		
21		813,975	813,975		
22					
23					
24					
25					
26					
27					
28					
29					
30					
31					
Explanation of group content	Germany preferred: User Group 1 800-814 MHz	Sweden preferred: license 800-814 MHz	Sweden preferred: license 800-814 MHz	Netherlands preferred: TV ch. 63 806-814 MHz	Netherlands preferred: TV ch. 63 806-814 MHz
Results for MK2	max. number	max. number	71% dif. to grp.22	max. number	43% dif. to grp.24
For use in ...	R2 setups only	R2 setups only	R2 setups only	R2 setups only	R2 setups only

### UHF-R6: 800 - 820 MHz, Group 1-12

	Group 1	Group 2	Group 3	Group 4	Group 5	Group 6	Group 7	Group 8	Group 9	Group 10	Group 11	Group 12
1	800,375	800,375	800,500	800,475	800,225	801,300	800,600	800,400	800,800	800,100	800,100	800,100
2	801,500	801,625	801,750	801,350	800,850	803,100	801,600	801,100	801,300	800,700	800,700	800,700
3	802,000	802,375	802,500	801,975	801,725	803,700	802,100	802,600	802,600	801,900	801,600	801,900
4	802,875	803,375	803,500	803,225	802,225	804,600	802,900	803,300	803,300	802,500	802,200	802,800
5	804,000	804,125	804,250	805,600	802,975	805,200	803,300	804,400	804,900	803,400	803,400	803,400
6	804,500	804,625	804,750	806,475	803,975	806,400	805,700	805,100	806,200	804,000	804,000	804,600
7	805,750	805,375	805,500	806,975	805,350	807,000	806,500	806,500	806,800	805,200	804,900	805,200
8	806,750	807,125	807,250	807,725	805,975	808,500	807,000	807,300	807,800	805,800	805,500	808,200
9	807,250	808,125	808,250	808,725	807,475	812,100	807,800	810,700	813,400	808,800	808,500	808,800
10	808,375	808,625	808,750	810,225	809,350	813,000	810,400	811,600	814,000	809,400	810,000	810,000
11	809,250	809,375	809,500	811,225	812,975	813,600	814,600	813,100	815,200	810,600	810,600	810,600
12	809,750	809,875	810,000	814,475	813,850	814,800	815,400	813,800	815,800	811,200	811,800	811,500
13	813,375	811,375	811,500	815,225	814,350	815,400	815,900	815,200	816,700	812,100	812,400	812,100
14	816,000	813,625	813,750	815,725	815,475	816,300	816,700	817,800	817,900	812,700	813,300	813,300
15	817,250	816,125	816,250	816,475	816,225	818,400	818,300	818,400	818,500	813,900	813,900	813,900
16	817,750	816,625	817,750	817,475	817,350	819,300	819,500	819,400	819,700	814,500	817,500	818,700
17	818,875	817,625	819,000	818,225	818,975							
18	819,750	818,875	819,775	819,475	819,725							
19		819,875										
20												
21												
22												
23												
24												
25												
26												
27												
28												
29												
30												
31												
Explanation of group content	Current MD group 1	Current MD group 2	Current MD group 3	Current MD group 4	Current MD group 5	Current MD group 6	Current MD group 7	Current MD group 8	Current MD group 9	Current MD group 10	Current MD group 11	Current MD group 12
Results for MK2												
For use in ...	MD/R6 setups	MD/R6 setups	MD/R6 setups	MD/R6 setups	MD/R6 setups	MD/R6 setups	MD/R6 setups	MD/R6 setups	MD/R6 setups	MD/R6 setups	MD/R6 setups	MD/R6 setups

### UHF-R6: 800 - 820 MHz, Group 13-23

	Group 13	Group 14	Group 15	Group 16	Group 17	Group 18	Group 19	Group 20	Group 21	Group 22	Group 23
1	800,250	800,100	800,100	800,400	800,175	800,100	800,250	800,100	806,025	806,250	806,025
2	800,550	800,550	800,550	800,700	800,925	800,550	801,000	800,550	806,325	806,700	806,475
3	801,000	801,225	801,450	801,375	801,375	801,300	801,450	801,450	807,000	807,000	806,775
4	801,300	801,750	802,650	801,900	801,975	801,900	802,350	801,900	807,300	807,600	807,375
5	801,900	802,050	803,100	802,200	802,725	802,350	802,800	803,100	807,825	807,900	807,675
6	802,650	802,725	804,000	802,800	803,175	802,950	803,550	803,550	808,125	808,350	808,125
7	803,100	803,100	804,600	803,550	803,925	803,850	804,000	804,150	808,800	808,650	808,425
8	803,700	803,850	806,250	804,750	804,825	804,450	805,050	804,600	809,100	809,250	809,025
9	804,150	804,750	806,700	805,050	806,025	805,200	805,500	805,800	810,750	810,750	810,525
10	805,350	805,200	807,300	805,500	806,625	805,650	806,250	806,250	811,050	811,350	811,125
11	805,800	805,500	807,600	806,100	807,075	806,700	807,600	807,150	811,725	811,650	811,425
12	806,700	807,000	808,050	806,925	807,975	807,300	808,050	808,800	812,025	812,100	811,875
13	808,350	811,050	809,550	811,275	808,575	809,250	808,800	809,550	812,550	812,400	812,175
14	809,100	811,650	810,900	812,625	809,025	809,700	809,400	810,000	812,850	813,000	812,775
15	811,650	812,550	811,350	813,300	809,625	810,900	810,300	810,900	813,525	813,300	813,075
16	812,250	812,925	812,700	813,600	810,375	811,350	810,900	811,650	813,825	813,750	813,525
17	812,700	814,500	813,900	814,350	810,825	811,950	811,950	812,100			
18	813,900	814,950	814,350	814,725	811,575	812,400	812,700	812,700			
19	814,350	815,550	814,950	816,300	812,475	813,150	813,150	813,150			
20	814,650	816,750	815,250	816,675	812,925	813,600	813,900	813,900			
21	815,850	817,200	816,300	817,275	813,825						
22	816,750	817,500	816,750	817,650							
23	818,175	818,400	817,050	818,475							
24	818,550	818,700	817,950	818,775							
25	819,300	819,150	818,400	819,450							
26	819,825	819,750	819,300								
27											
28											
29											
30											
31											
Explanation of group content	Full Range, max. # of compatible frequencies	Full Range, max. # of compatible frequencies	Full Range, max. # of compatible frequencies	Full Range, max. # of compatible frequencies	Sweden preferred: license 800-814 MHz	Sweden preferred: license 800-814 MHz	Sweden preferred: license 800-814 MHz	Sweden preferred: license 800-814 MHz	Netherlands preferred: TV ch. 63 806-814 MHz	Netherlands preferred: TV ch. 63 806-814 MHz	Netherlands preferred: TV ch. 63 806-814 MHz
Results for MK2	max. number	91% dif. to grp.13	65% dif. to grp.13	88% dif. to grp.13	max. number	95% dif. to grp.17	95% dif. to grp.17	95% dif. to grp.17	max. number	88% dif. to grp.21	81% dif. to grp.21
For use in ...	R6 setups only	R6 setups only	R6 setups only	R6 setups only	R6 setups only	R6 setups only	R6 setups only	R6 setups only	R6 setups only	R6 setups only	R6 setups only

### UHF-S2: 838 - 862 MHz, Group 1-12

	Group 1	Group 2	Group 3	Group 4	Group 5	Group 6	Group 7	Group 8	Group 9	Group 10	Group 11	Group 12
1	854,900	854,900	855,525	855,900	846,875	848,125	843,000	839,250	842,375	839,250	<b>838,300</b>	<b>838,075</b>
2	855,900	855,275	856,525	856,650	847,875	849,250	846,000	840,750	843,000	840,250	<b>839,050</b>	<b>838,825</b>
3	856,575	855,900	857,025	857,150	848,375	849,875	847,000	841,375	844,750	841,000	<b>839,650</b>	<b>839,425</b>
4	857,125	856,175	857,775	858,025	849,625	850,750	847,625	843,000	845,250	844,375	<b>840,550</b>	<b>840,625</b>
5	858,025	856,575	858,775	858,650	851,125	851,250	848,500	843,750	852,875	845,500	<b>842,200</b>	<b>841,225</b>
6	858,650	857,625	859,400	859,650	851,875	852,000	850,375	845,000	853,875	846,125	<b>842,650</b>	<b>842,125</b>
7	859,625	857,950	860,275	860,400	853,500	853,000	852,000	845,750	854,625	847,625	<b>843,700</b>	<b>842,575</b>
8	860,400	858,200	860,775	860,900	854,875	853,625	854,250	847,500	855,125	848,875	<b>844,300</b>	<b>844,075</b>
9	860,900	858,650	861,525	861,650	856,625	855,500	856,750	848,000	855,875	851,125	<b>845,050</b>	<b>844,675</b>
10	861,750	860,400	855,025	854,900	858,125	857,000	857,500	850,500	856,875	852,500	<b>845,500</b>	<b>845,125</b>
11		860,900			858,875	857,625	858,750	851,625	858,375	854,250	<b>847,150</b>	<b>846,475</b>
12		861,200			859,375	858,750	859,750	853,875	859,500	854,875	<b>848,200</b>	<b>849,175</b>
13		861,550			860,375	859,375	860,375	855,000	860,250	855,750	<b>849,400</b>	<b>849,775</b>
14		861,750			860,875	860,750	861,250	855,500	861,250	857,625	<b>850,150</b>	<b>850,225</b>
15					861,625	861,375	861,750	857,750	861,875	858,250	<b>850,750</b>	<b>852,475</b>
16					846,375	847,500	842,500	838,750	841,500	838,625	<b>853,000</b>	<b>853,375</b>
17											<b>853,450</b>	<b>853,825</b>
18											<b>854,950</b>	<b>854,575</b>
19											<b>855,400</b>	<b>855,025</b>
20											<b>856,300</b>	<b>855,625</b>
21											<b>857,050</b>	<b>856,075</b>
22											<b>857,950</b>	<b>857,275</b>
23											<b>858,400</b>	<b>858,025</b>
24											<b>859,000</b>	<b>858,625</b>
25											<b>859,450</b>	<b>859,075</b>
26											<b>860,200</b>	<b>860,575</b>
27											<b>860,800</b>	<b>861,325</b>
28											<b>861,550</b>	<b>861,775</b>
29												
30												
31												
<b>Explanation of group content</b>	Current KK group 1	Current KK group 2	Current KK group 3	Current KK group 4	Current KK group 5	Current KK group 6	Current KK group 7	Current KK group 8	Current KK group 9	Current KK group 10	<b>Full Range, max. # of compatible frequencies</b>	<b>Full Range, max. # of compatible frequencies</b>
Results for MK2	KK/S2 setups										max. number	group11 + 75kHz
For use in ...	KK/S2 setups	KK/S2 setups	KK/S2 setups	KK/S2 setups	KK/S2 setups	KK/S2 setups	KK/S2 setups	KK/S2 setups	KK/S2 setups	KK/S2 setups	S2 setups only	S2 setups only

### UHF-S2: 838 - 862 MHz, Group 13-24

	Group 13	Group 14	Group 15	Group 16	Group 17	Group 18	Group 19	Group 20	Group 21	Group 22	Group 23	Group 24
1	838,750	839,475	838,250	838,300	838,350	838,400	838,100	838,100	838,075	846,075	854,075	855,675
2	840,400	840,625	839,900	839,950	838,750	838,800	840,050	839,050	838,375	846,675	854,375	856,375
3	840,850	841,100	840,325	840,950	841,000	841,050	840,800	839,750	838,975	846,975	854,975	856,800
4	841,450	842,525	840,900	841,775	841,825	841,875	841,325	840,175	839,275	847,575	855,275	857,425
5	841,900	843,575	841,725	842,875	842,925	842,975	842,425	840,750	840,025	848,025	855,725	860,600
6	842,650	844,800	842,825	843,400	844,675	844,725	843,825	841,575	840,325	848,325	856,025	
7	843,100	845,750	843,350	844,150	845,650	845,700	844,250	842,675	840,925	848,925	856,625	
8	843,700	846,900	844,100	844,625	847,300	847,350	844,950	843,200	841,225	849,225	856,925	
9	845,200	847,475	844,575	845,600	851,450	851,500	845,500	843,950	843,025	851,025	858,725	
10	845,650	849,425	854,250	848,950	854,350	854,400	845,900	844,425	843,325	851,325	859,325	
11	847,150	849,950	855,200	853,600	854,750	854,800	846,600	845,400	843,925	851,925	859,625	
12	848,350	851,550	855,900	854,300	855,300	855,350	848,800	845,900	844,225	852,225	860,075	
13	849,250	852,850	856,325	854,700	856,425	856,475	854,100	853,400	844,675	852,675	860,675	
14	851,950	854,900	856,900	855,250	857,000	857,050	854,600	854,100	844,975	852,975	861,050	
15	852,700	856,600	857,725	855,950	857,825	857,875	855,575	854,500	845,575	853,575	861,575	
16	853,150	857,125	858,825	856,375	858,925	858,975	856,050	855,750	845,875	853,875	861,875	
17	853,750	857,975	859,350	857,775	859,450	859,500	857,325	856,175				
18	854,500	858,575	860,100	858,875	860,675	860,725	858,425	856,750				
19	854,950	859,025	860,575	859,400	861,650	861,700	859,250	857,575				
20	856,000	859,675		860,150			859,825	858,675				
21	856,450	861,200		860,625			860,250	859,200				
22	857,350	861,800					860,950	859,950				
23	857,800						861,900	861,900				
24	858,550											
25	859,000											
26	859,900											
27	860,500											
28	861,400											
29												
30												
31												
Explanation of group content Results for MK2	Full Range, max. # of compatible frequencies	Germany preferred: User Group 4 838-862 MHz	Germany preferred: User Group 3A 838-862 MHz	Germany preferred: User Group 3B 838-862 MHz	Germany preferred: User Group 3C 838-862 MHz	Germany preferred: User Group 3D 838-862 MHz	Germany preferred: User Group 2 838-862 MHz	Germany preferred: User Group 1 838-862 MHz	Optimized TV channels: TV ch. 67 838-846 MHz	Optimized TV channels: TV ch. 68 846-854 MHz	Optimized TV channels: TV ch. 69 854-862 MHz	U.K. preferred: "CH69 Co-ordinated" SET 1
Results for MK2	82% dif. to grp.11	max. number	max. number	max. number	max. number	max. number	max. number	max. number	max. number	max. number	max. number	fixed frequencies
For use in ...	S2 setups only	S2 setups only	S2 setups only	S2 setups only	S2 setups only	S2 setups only	S2 setups only	S2 setups only	S2 setups only	S2 setups only	S2 setups only	S2 setups only

### UHF-S2: 838 - 862 MHz, Group 25-28

	Group 25	Group 26	Group 27	Group 28
1	856,500	854,625	854,325	854,325
2	857,500	854,925	854,775	854,625
3	858,250	855,525	855,525	855,075
4	858,700	855,825	856,125	855,375
5	859,525	856,275	856,425	855,975
6		856,575	856,875	856,275
7		857,175	857,175	856,725
8		857,475	857,775	857,025
9		858,975	859,750	859,900
10		859,275	860,200	860,200
11		859,875	860,500	860,800
12		860,175	860,950	861,100
13		860,625	861,550	861,550
14		860,925	861,925	861,850
15		861,525		
16		861,825		
17				
18				
19				
20				
21				
22				
23				
24				
25				
26				
27				
28				
29				
30				
31				
Explanation of group content Results for MK2				
Results for MK2	U.K. preferred: "CH69 Co-ordinated" SET 2	U.K. preferred: "Co-ordinated frequencies" INDOORS	U.K. preferred: "Co-ordinated frequencies" OUTDOORS	U.K. preferred: "Co-ordinated frequencies" OUTDOORS
For use in ...	fixed frequencies	max. number	max. number	79% dif. to grp.24
	S2 setups only	S2 setups only	S2 setups only	S2 setups only