

PGX - P6: 702 - 720 MHz

CHAN	Ch 1 - 9	Ch 11-19	Ch 21-29	Ch 31-39	Ch 41-49	Ch 51-59	Ch 61-69	Ch 71-79	Ch 81-89	Ch 91-99
1	702,200	710,200	703,750	703,650	702,750	703,750	702,100	704,775	702,300	703,000
2	703,300	711,300	705,975	705,650	704,500	705,750	704,025	706,225	704,975	706,025
3	704,700	712,700	707,200	708,650	705,750	708,250	705,500	710,500	706,775	708,000
4	705,800	713,800	708,850	710,875	708,250	711,750	708,500	712,025	709,100	710,300
5	707,675	715,675	710,950	712,450	711,250	714,500	710,100	714,225	710,300	712,225
6	708,775	716,775	712,425	715,125	712,500	715,750	712,025	716,900	712,225	716,000
7			714,325	717,025	715,250	718,750	713,500	718,500	714,775	717,100
8			717,000	718,500	718,750		717,300		716,700	719,000
9			718,575							
	Optimized TV channels: TV ch. 50 702-710 MHz (same as SLX-P4 group 10)	Optimized TV channels: TV ch. 51 710-718 MHz (same as SLX-P4 group 11)	Full Range max. # of compatible frequencies (same as part of SLX-P4 group 2)	Full Range max. # of compatible frequencies (same as part of SLX-P4 group 3)	France preferred: User Group A (option 1, same as part of SLX-P4 group 4)	France preferred: User Group A (option 2, same as part of SLX-P4 group 5)	France preferred: User Group B (option 1, same as part of SLX-P4 group 6)	France preferred: User Group B (option 2, same as part of SLX-P4 group 7)	France preferred: User Group C (option 1, same as part of SLX-P4 group 8)	France preferred: User Group C (option 2, same as part of SLX-P4 group 9)